

# PURO™

UV Disinfection Lighting



*Portable UV Protection*

## User Manual Sentry M1 and M2-T Fixtures

with Single or Dual  
UV Light Engines



**Safety Warnings**



WARNING: TO REDUCE THE RISK OF FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE THIS UNIT TO RAIN OR MOISTURE.

CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE COVER. NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.



The lightning flash with arrowhead symbol, within an equilateral triangle is intended to alert the user to the presence of uninsulated “dangerous voltage” within the product’s enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

**Important Safety Notes**

Read these instructions prior to operating the fixture. Keep and follow all instructions.

- Heed all warnings. Failure to use the equipment in the manner specified may impair the fixture from providing the desired protection.
- Plug unit into a grounded outlet. Ensure proper conditions for operation. The unit is designed to operate under normal conditions indoors (temperature 5-40 degrees Celsius, RH less than 80% (non-condensing), at an altitude <2000m and main supply fluctuations +/- 10% of nominal voltage, over voltage Category II.
- Allow unit to complete pre-programmed cycles prior to unplugging or shutting off power. This allows it to enter safe mode.
- Do not allow the unit to get wet or use in or near water.
- Do not block any ventilation openings. Use in accordance with these instructions.
- Do not attempt to open or tamper with the unit.
- Do not place or store the unit near any flammable materials or liquids.
- Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
- Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the unit.
- Unplug this unit during lightning storms or when unused for long periods of time.
- Refer all servicing to the manufacturer if there is any damage to the unit or it is not operating correctly.
- The fixture is designed to operate only when the room is unoccupied. There are redundant safety systems to ensure the unit does not activate while the room is occupied as the UV light is not recommended for excessive exposure. If the sensor in the system fails, the system will shut down.
- Do not look directly at the unit due to the brightness of the light. UV light does not significantly penetrate standard glass, therefore, incidental exposure on the other side of a window or wall does not present any significant risk.
- KEEP AWAY FROM CHILDREN

## UV Safety Overview

Given the correct combination of user protocols and the built-in safety features of the unit, there are minimal risks of any harmful effects from using the unit.

### Recommendations

- If in the vicinity of the Sentry M1 or M2-T units during operation, do not look directly at the light. This is similar to how one would avoid harmful effects from the sun by not looking directly at it.
- UV light does not significantly penetrate standard glass. It is safe to be behind a window or wall while the unit is operational.
- Per the built-in safety features described below, the unit is designed to not operate while a room is occupied. However, operators are instructed in the user manual to have all persons vacate a space before operation. Further optional protocols, such as signage indicating the UV unit is in operation may be desired.

### Safety Features

The Sentry M1 and M2-T have four primary aspects to their built-in safety features to ensure the safety of anyone operating or in the vicinity of a unit.

#### Limited Exposure Risk

Due to the nature of the programming on the Sentry unit, over a 30-minute cycle time for the fixture, the actual exposure to UV (if there were no other safety systems in place) would be no more than two seconds of exposure – well below the recommended standards. Furthermore, this is approximately 1800x less time exposure than would occur from the sun if outdoors for 30 minutes.

#### Redundant Safety Systems

Each Sentry unit has a built-in passive infrared (PIR) sensor used to detect motion in a space. The sensor is programmed to detect individuals walking into the deployment space. The unit will not resume operation of the cleaning cycle until it has successfully detected the space is free of motion.

#### Safe Stop

The third layer of protection built into the Sentry unit is to ensure that if the motion sensor or other components experience technical issues, the unit will safe stop by cycling the unit off. The unit will flash red indicating that one should contact PURO Lighting for technical support. The unit will not resume operation until the issue detected has been resolved. If unit is non-responsive (i.e. non-operational or no indicator light), contact PURO Lighting for technical support.

#### Frequency of Flashes

The Sentry unit will flash every 6 seconds during operation. Violet Defense, PURO Lighting's technology partner, collaborated with the Epilepsy Foundation when designing the product to ensure that the frequency of flashes will not cause any issues for someone with photosensitive epilepsy.

**Disclaimer:** The Sentry unit is not intended for use as a medical device and people should not be directly exposed to the light generated by the unit. The actual disinfection rates on a specific space will vary.

## Governmental Guidelines for UV Light Safety

### Occupational Safety and Health Administration (OSHA)

The Occupational Safety and Health Administration (OSHA) does not have any mandated exposure limits to ultraviolet light. OSHA only provides technical guidance regarding protecting employees from ultraviolet laser exposure. While general information about ultraviolet contained in that guidance is described below, it is important to note that PURO Lighting does not currently deploy ultraviolet lasers. For more information on OSHA's guidelines, visit:

<https://www.osha.gov/laws-regs/standardinterpretations/2003-02-26>.

Ultraviolet radiation is divided into three regions: UV-A: 315-400 nanometers (nm), UV-B: 280-315 nm, and UV-C: 200-280 nm. UV can be associated with adverse health effects due to prolonged exposure and the wavelength of light.

According to OSHA's guidelines, "exposure in the shorter UV-C and longer UV-A ranges seems less harmful to human skin. The shorter wavelengths are absorbed in the outer dead layers of the epidermis and the longer wavelengths have an initial pigment-darkening effect followed by erythema if there is exposure to excessive levels."

"The hazards associated with skin exposure are of less importance than eye hazards." Exposure to light may cause photokeratitis or cataracts.

### National Institute for Occupational Safety and Health (NIOSH)

The National Institute for Occupational Safety and Health (NIOSH) recommends limits to exposure determined by the wavelength of UV light and intensity. NIOSH recommends that the time of exposure to an intensity of 100 microwatts per square centimeter at wavelength 254 nm not exceed 1 minute. Per the programming, UV exposure from Sentry units for a 30-minute cycle is less than two seconds. For more information, view the recommended standards from NIOSH at:

<https://www.cdc.gov/niosh/docs/73-11009/pdf/73-11009A.pdf>.

### Environmental Protection Agency (EPA)

The Environmental Protection Agency (EPA) is the governmental agency responsible for regulating ultraviolet light products. It regulates chemical disinfectants along with devices, such as equipment that generates UV light, used to control pests like bacteria and making antimicrobial claims. The manufacturer of PURO Lighting products is an EPA-registered company (Facility No. 92142) and is in full compliance with all regulations. For more information about EPA guidelines, visit:

<https://www.epa.gov/safepestcontrol/pesticide-devices-guide-consumers>.

### Food and Drug Administration (FDA)

The Food and Drug Administration (FDA) only regulates devices that are classified as medical instruments, machines, and devices used to treat diagnosed medical conditions. Therefore, PURO Lighting does not fall under FDA guidelines. Furthermore, PURO Lighting products do use materials approved by the FDA for use in food and medical applications.

## Operation of Unit

Built-in motion sensor will actively monitor the space and only allow the unit to activate when the space is unoccupied.



Sentry M1 or M2-T Units - Use Pulsed Xenon technology to deploy powerful bursts of UV-C, UV-B, UV-A, and violet-blue light with 170° of coverage for the Sentry M1-1 and M2-T units and 340° for the Sentry M1-2 unit.

The height of each whole room unit may be repositioned to optimize the disinfecting of your space.

### 1. Position the unit in the targeted cleaning area.

- It is recommended that you place the unit approximately 2 meters (~6 1/2 feet) or less away from the priority areas. Note that the unit can effectively kill pathogens up to 4 meters (~13 feet) away, but the length of time necessary to run the unit increases proportionately to the distance from targeted area.
- Leverage reflective surfaces in your space, including standard glass, as the UV light will reflect off of these surfaces increasing their germ-killing effects. However, surfaces such as paint will absorb the photons, minimizing effects of the unit, so avoid placing the unit too close to walls in your area.

### 2. Adjust the height of the unit to optimize effects of the unit, minimizing any shadowed areas (unit can only kill germs where the light touches, either directly or by reflection). See page 6 for how to adjust height of unit.

### 3. Plug in the unit, which runs at 120V AC and 60 Hz. Once powered on, at its peak, the unit will draw up to 7 amps (less than a standard vacuum cleaner) for 4 second intervals. Ensure the breaker has available amp draw during operation.

### 4. While the unit is operational, all personnel should leave the room during the cleaning cycle. Exit the room within 60 seconds for optimal functioning of the unit. The unit is programmed to operate for 30 minutes per cycle. The unit's redundant safety systems will stop the unit from operating if motion is detected in the space. The unit will resume operation approximately 60 seconds after room is unoccupied and no additional motion is detected.

### 5. The unit will run a safety test to ensure unit is functioning properly and that there is no motion detected in the space. If successful, unit will run its pre-programmed operational cycle as described in step 4.

### 6. Allow the unit to complete its entire cycle before unplugging the unit. This allows the unit to enter safe mode. If necessary to unplug the unit prior to completion of cleaning cycle, be sure to keep unit away from water for optimal safety.

### 7. Once the cycle is complete reposition the unit within the space, as necessary, to account for any shadowing that would have occurred during the first cycle.

\*It is recommended that after every 30-minute run that you allow the unit to cool down for a 15-minute period of time, in order to maximize the life expectancy of your PURO Lighting Sentry M1 or M2-T product.



## SETTING UP TRIPOD STAND




1. Position the stand in the target area. Rotate knob counterclockwise to loosen.
2. Pull on legs to spread apart to desired position.
3. Rotate knob clockwise to tighten.

## ADJUSTING HEIGHT OF VERTICAL POLE ON STAND



1. Rotate upper knob counterclockwise to loosen.
2. Raise the vertical pole to desired height.
3. Rotate knob clockwise to tighten.
4. Insert security key into slot (optional).

## SECURING UNITS TO STAND



1. Align bracket on back of units with bracket on stand. Slide down until fully seated.
2. Insert screw and tighten to lock unit onto stand.
3. The mounting bracket swivels enabling unit to be positioned vertically or horizontally by turning unit to desired direction.

## Guidelines for Cleaning the Fixture

- To clean the unit, wipe down the metal plates with stainless steel polish using a microfiber cloth.
- Do not use abrasive cleaners to clean the unit.

For most situations, the instructions above can be used to clean the unit. However, there are special instructions recommended for blood spills, or when certain organisms, such as *C. diff* are known or suspected to be present.

## GENERAL DISINFECTION GUIDELINES

1. Complete standard cleaning procedures to remove any visible dirt, grease, or other debris from space.
2. Activate unit per operational instructions above.
3. Upon returning to space, look at indicator light. Solid green light indicates cleaning cycle completed. If motion was detected prior to observing the indicator light, the indicator light will turn red. If users want to determine if the unit completed the last cycle, prior to powering off, stand out of range of the motion sensor for 60 seconds. The light will resume solid green if cycle was completed. Otherwise, it will resume operation.

## Cleaning when Blood or Bodily Fluids are Present

UV light has the ability to penetrate liquid blood, which has not formed a dried crust, or bodily fluids up to a 1/16" thickness as long as there is no tissue or solid material present. Therefore, UV light may be used to help protect staff before and after traditional cleaning protocols for your facility.

1. Activate the fixture prior to commencing any cleaning procedures. If the blood has already dried, apply hydrogen peroxide solution prior to running the unit.
2. Utilize normal procedures, including appropriate safety protocols to clean the space, including removal of blood and bodily fluids.
3. Activate a second cycle of the fixture to target any remaining bacteria and viruses.

## Cleaning when *C. diff* is of Concern

*Clostridium difficile* (*C. diff*) is a bacteria that is extremely difficult to kill as it is able to survive in unfavorable conditions. Furthermore, it is an anaerobic, endosporic organism, which means it can survive without oxygen and form dormant spores to survive harsh conditions. With the risk of severe illness associated with *C. diff*, it is recommended that you use a combination of approaches to reduce the risk of contracting *C. diff* in your facility.


1. Utilize your facility's adopted environmental cleaning and disinfection strategy for dealing with *C. diff*.
2. Activate the fixture for two consecutive 30-minute cycles at a range of less than one meter for best results, or up to 2 hours for ceiling mounted units (must have a 30-minute break between two 60-minute cycles).

## Operational Mode

By default, your unit will be configured in single cycle mode for a 30-minute run time.

- **Single Cycle Mode:** In this method, users will manually activate the unit to start a disinfection cycle. The unit will then run its pre-programmed cycle (i.e. 15 or 30 minutes) one time before entering safe mode until power is cycled on and off again. Users may select the timeout time, which determines how long the unit will wait until resuming operation after motion is detected.

## Sensor Indicators



Each unit has an indicator light that helps you determine the status of the unit.

Color of Light	Meaning
Flashing Green	Unit is ready to begin cleaning when room becomes unoccupied.
Solid Green	Unit has successfully completed its cleaning cycle.
Solid Red	Unit was interrupted during the cleaning cycle. Cleaning will resume when room becomes unoccupied again during the programmed times for operation.
Flashing Red	One of the safety sensors has detected an issue. Please see troubleshooting section for further information.

## Troubleshooting

1. If unit is flashing red, then an issue was detected by the safety sensors. Unplug the unit.
2. Plug the unit back into the wall. Exit the room within 60 seconds.
3. When you return to the room, identify the color of light on the sensor indicator. If unit is green or solid red, the unit is working properly. If unit is still flashing red, contact PURO Lighting technical support.
4. If unit is non-responsive (i.e. no indicator light showing), please contact PURO Lighting technical support.

## Technical Support

Email us at [support@purolighting.com](mailto:support@purolighting.com) or call (877) 452-8785.